

LoRaWAN® Concentrator Card based on Semtech SX1303 Core Cell Design in Mini PCIe Form Factor

The n-fuse LRWCC3-MPCIE family of cards enable OEMs and system integrators to build high-performance, certified LoRaWAN® gateway solutions. Moreover it allows to retrofit existing routers and other edge-level network equipment with LoRaWAN® gateway capabilities.

Key Features

- Compact size
- Broad usage spectrum through standard mini PCIe form factor
- USB host interface (through mini PCIe) or UART
- Alternative SPI/I2C/GPIO host interface (non mini PCIe compatible)
- SX1302/3 digital base band proc. and 2x SX1250 and 1x SX1261 Tx/ Rx front-ends
- Listen before talk
- Output power level up to +27 dBm
- Firmware upgradeable via USB DFU
- Low power consumption

Application Areas

- Internet of Things (IoT) and Industrial Internet of Things (IIoT) Applications
- Machine to Machine (M2M)
- Smart City
- Agricultural Monitoring
- Home-, Building-, Industrial Monitoring and Control
- Remote Control
- Wireless Alarm and Security Systems
- Tracking Applications


Specifications

Category	Feature	Description
General Radio	Semtech Radios	2x SX1250 and 1x SX1261
Connectors	Connector Type	Mini PCI Express (full length)
	External Antenna	U.FL connector 50 Ω impedance
Host Interface		USB version 2 or greater (default) SPI/ I2C/ GPIO
Power	Input Voltage	3.3 VDC +/- 5%
	Consumption	TX max, +27 dBm: 464 mA TX typical, +14 dBm: 209 mA RX (all channels): 50 mA Idle: 17 mA
RF	Frequency Range	863 to 870 MHz ^a 915 to 928 MHz ^b
	Sensitivity	^a less or equal than -125 dBm at SF7, BW 125KHz less or equal than -140 dBm at SF12, BW 125KHz ^b less or equal than -125 dBm at SF7, BW 125KHz less or equal than -140 dBm at SF12, BW 125KHz
	Max RF Output Power	Up to +27 dBm
Features	Fine Time Stamping ^c	Enabling Time Difference of Arrival (TDOA) network-based geolocation.
	Listen Before Talk	Prevents collisions while accessing the spectrum.
Modulation	LoRa [®]	
Status Indication	LEDs	Red: Rx Yellow: Tx Green: Config OK Power
Host Software	HAL User Space Driver and Packet Forwarder	https://github.com/Lora-net/sx1302_hal
Firmware	For MCU (STM32)	USB: https://github.com/Lora-net/sx1302_hal/tree/master/mcu_bin

Category	Feature	Description
Operating Conditions	Temperature (operating)	-40 to +85° C The Tx power rises with lower temperatures but is automatically compensated.
	Humidity	10% ~ 90% RH Non-condensing
Physical Properties	Dimensions WxHxD	51 x 30 x 4 mm (device) 51 x 30 x 1 mm (PCB)
	Weight	9 g
Regulatory	Certifications	CE (Radio Equipment Directive 2014/53/EU) ^a FCC ID: 2AY53LRWCC3915 ISED:
	Materials	RoHS, REACH
Warranty		12 months for B2B customers 24 months for B2C customers

^a for 868 Mhz, ^b for 915 Mhz, ^c SX1303 only

Block Diagram



Interfaces

Mini-PCIe Connector

The concentrator card is compliant with the mini PCIe specification and can thus be used in any compatible host system. Some reserved pins are used and others re-purposed as shown in the following table.

Pin #	Symbol	Type	Description
1	NC	-	
2	VCC	power	
3	NC	-	
4	GND	power	
5	NC	-	
6	GPIO6	Input/ output	General purpose IO from MCU

Pin #	Symbol	Type	Description
7	NC	-	
8	NC	-	
9	GND	power	
10	NC	-	
11	NC	-	
12	NC	-	
13	NC	-	
14	NC	-	
15	GND	power	
16	ENABLE	input	Power enable the device (active high)
17	HOST_SCK	input	SPI clock
18	GND	power	
19	HOST_MISO	output	SPI MISO
20	NC	-	
21	GND	power	
22	SX130x_RESET	input	SX130x reset signal (active high)
23	HOST_MOSI	input	SPI MOSI
24	VCC	power	
25	HOST_CSN	input	SPI CSN
26	GND	power	
27	GND	power	
28	SX130x_GPIO_8	input	SX130x GPIO8
29	GND	power	
30	I2C_SCL	input	MCU/ temperature sensor I2C bus clock
31	PPS	input	Pulse per second signal usually from GNSS devices for accurate timing.
32	I2C_SDA	input/ output	MCU/ temperature sensor I2C bus data
33	NC	-	
34	GND	power	
35	GND	power	
36	USB_D- / Tx	input/ output	USB data - / UART Rx
37	GND	power	
38	USB_D+ / Rx	input/ output	USB data + / UART Tx
39	VCC	power	
40	GND	power	
41	VCC	power	
42	NC	-	
43	GND	power	

Pin #	Symbol	Type	Description
44	SX1261_NSS	input	SX1261 SPI NSS
45	SWCLK	input	STLink clock
46	SX1261_DIO1	input	SX1261 DIO1
47	SWDIO	input/ output	STLink serial I/O line
48	SX1261_NRESET	input	SX1261 reset signal (active low, on device pull-up)
49	MCU_NRESET	input	MCU reset signal (active low, on device pull-up)
50	GND	power	
51	MCU_BOOT0	Inout	MCU boot0 signal (active high, on device pull-down)
52	VCC	power	

NC = Not Connected
VCC = 3.3 V Power Supply
GND = Ground

RF IO Port

The RF IO port is a U.FI type connector for the connection to the antenna. Usually a 'pigtail' cable with a U.FI to SMA or N-Type connector is used for this.

⚠ Note: that the device must not be used without a proper 50 Ohm load on the RF IO port.

Product Family Portfolio

The lrwcc3-mpcie-s-xxx parts come without the STM32 MCU and can thus be only driven by SPI/ I2C/ GPIO.

Part Number	Description	Availability
lrwcc2-mpcie-868	SX1302 based 868 MHz variant	discontinued
lrwcc2-mpcie-915	SX1302 based 915 MHz variant	discontinued
lrwcc3-mpcie-868	SX1303 based 868 MHz variant	available
lrwcc3-mpcie-915	SX1303 based 915 MHz variant	available
lrwcc3-mpcie-s-868	SX1303 based 868 MHz, SPI variant	available
lrwcc3-mpcie-s-915	SX1303 based 915 MHz, SPI variant	available
lrwcc3-mpcie-433	SX1303 based 433 MHz variants	available

Ordering Information

All n-fuse products can be ordered directly through the n-fuse website. You can also contact a sales representative via devices-sales@n-fuse.co for volume ordering.

n-fuse RESERVES THE RIGHT TO CHANGE PRODUCTS, INFORMATION AND SPECIFICATIONS WITHOUT NOTICE. Products and specifications discussed herein are for reference purposes only. All information discussed herein is provided on an "AS IS" basis, without warranties of any kind. This document and all information discussed herein remain the sole and exclusive property of n-fuse. No license of any patent, copyright, mask work, trademark or any other intellectual property right is granted by one party to the other party under this document, by implication, estoppel or other-wise. n-fuse products are not intended for use in life support, critical care, medical, safety equipment, or similar applications where product failure could result in loss of life or personal or physical harm, or any military or defence application, or any governmental procurement to which special terms or provisions may apply. For updates or additional information about n-fuse products, contact us. Product names, logos, brands, and other trademarks featured or referred are the property of their respective trademark holders.

Version 11.08.2023

© 2023 n-fuse GmbH, All rights reserved.